

## ISL59910, ISL59913

Triple Differential Receiver/Equalizer

FN6406  
Rev 1.00  
Sep 28, 2018

The [ISL59910](#) and [ISL59913](#) are triple channel differential receivers and equalizers. They each contain three high speed differential receivers with five programmable poles. The outputs of these pole blocks are then summed into an output buffer. The equalization length is set with the voltage on a single pin. The ISL59910 and ISL59913 output can also be put into a high impedance state, enabling multiple devices to be connected in parallel and used in multiplexing applications.

The gain can be adjusted up or down on each channel by 6dB using the  $V_{GAIN}$  control signal. In addition, a further 6dB of gain can be switched in to provide a matched drive into a cable.

The ISL59910 and ISL59913 have a bandwidth of 150MHz and consume just 108mA on  $\pm 5V$  supply. A single input voltage sets the compensation levels for the required length of cable.

The ISL59910 is a special version of the ISL59913 that decodes syncs encoded onto the common modes of three pairs of CAT-5 cable by the EL4543 refer to the EL4543 datasheet for details.

The ISL59910 and ISL59913 are available in a 28 Ld QFN package and are specified for operation across the full  $-40^{\circ}C$  to  $+85^{\circ}C$  temperature range.

### Features

- 150MHz -3dB bandwidth
- CAT-5 compensation
  - 100MHz at 600ft
  - 135MHz at 300ft
- 108mA supply current
- Differential input range: 3.2V
- Common-mode input range: -4V to +3.5V
- $\pm 5V$  supply
- Output to within 1.5V of supplies
- Available in 28 Ld QFN package
- Pb-free plus anneal available (RoHS compliant)

### Applications

- Twisted-pair receiving/equalizer
- KVM (Keyboard/Video/Mouse)
- VGA over twisted-pair
- Security video

### Related Literature

For a full list of related documents, visit our website:

- [ISL59910](#) and [ISL59913](#) product pages


## Ordering Information

| PART NUMBER<br>(Notes 2, 3) | PART MARKING     | TAPE AND REEL<br>(UNITS) (Note 1) | PACKAGE<br>(RoHS Compliant) | PKG.<br>DWG. # |
|-----------------------------|------------------|-----------------------------------|-----------------------------|----------------|
| ISL59910IRZ                 | 59910 CRZ        | -                                 | 28 Ld QFN                   | L28.4x5        |
| ISL59910IRZ-T7              | 59910 CRZ        | 1k                                | 28 Ld QFN                   | L28.4x5        |
| ISL59913IRZ                 | 59913 IRZ        | -                                 | 28 Ld QFN                   | L28.4x5        |
| ISL59913IRZ-T7              | 59913 IRZ        | 1k                                | 28 Ld QFN                   | L28.4x5        |
| ISL59913IRZ-EVALZ           | Evaluation Board |                                   |                             |                |
| ISL59910IRZ-EVALZ           | Evaluation Board |                                   |                             |                |

NOTES:

1. Refer to [TB347](#) for details about reel specifications.
2. Pb-free plus anneal products employ special Pb-free material sets; molding compounds/die attach materials and 100% matte tin plate termination finish, which are RoHS compliant and compatible with both SnPb and Pb-free soldering operations. Pb-free products are MSL classified at Pb-free peak reflow temperatures that meet or exceed the Pb-free requirements of IPC/JEDEC J STD-020.
3. For Moisture Sensitivity Level (MSL), see the [ISL59910](#) and [ISL59913](#) product information pages. For more information about MSL, see [TB363](#).

## Pinouts



EXPOSED DIEPLATE SHOULD BE CONNECTED TO -5V

## Pin Descriptions

| PIN NUMBER | ISL59910 |  | ISL59913 |  |
|------------|----------|--|----------|--|
|            | PIN NAME | PIN FUNCTION                             | PIN NAME | PIN FUNCTION                             |
| 1          | VSMO_B   | -5V to blue output buffer                | VSMO_B   | -5V to blue output buffer                |
| 2          | VOUT_B   | Blue output voltage referenced to 0V pin | VOUT_B   | Blue output voltage referenced to 0V pin |
| 3          | VSPO_B   | +5V to blue output buffer                | VSPO_B   | +5V to blue output buffer                |
| 4          | VSPO_G   | +5V to green output buffer               | VSPO_G   | +5V to green output buffer               |

**Pin Descriptions** (Continued)

| PIN NUMBER  | ISL59910 |   | ISL59913 |   |
|-------------|----------|---|----------|---|
|             | PIN NAME | PIN FUNCTION  | PIN NAME | PIN FUNCTION  |
| 5           | VOUT_G   | Green output voltage referenced to 0V pin   | VOUT_G   | Green output voltage referenced to 0V pin   |
| 6           | VSMO_G   | -5V to green output buffer  | VSMO_G   | -5V to green output buffer  |
| 7           | VSMO_R   | -5V to red output buffer  | VSMO_R   | -5V to red output buffer  |
| 8           | VOUT_R   | Red output voltage referenced to 0V pin   | VOUT_R   | Red output voltage referenced to 0V pin   |
| 9           | VSPO_R   | +5V to red output buffer  | VSPO_R   | +5V to red output buffer  |
| 10          | VCTRL    | Equalization control voltage (0V to 0.95V)  | VCTRL    | Equalization control voltage (0V to 0.95V)  |
| 11          | VREF     | Reference voltage for logic signals, V <sub>CTRL</sub> , and V <sub>GAIN</sub> pins | VREF     | Reference voltage for logic signals, V <sub>CTRL</sub> , and V <sub>GAIN</sub> pins |
| 12          | VGAIN_R  | Red channel gain voltage (0V to 1V)   | VGAIN_R  | Red channel gain voltage (0V to 1V)   |
| 13          | VGAIN_G  | Green channel gain voltage (0V to 1V)   | VGAIN_G  | Green channel gain voltage (0V to 1V)   |
| 14          | VGAIN_B  | Blue channel gain voltage (0V to 1V)  | VGAIN_B  | Blue channel gain voltage (0V to 1V)  |
| 15          | VSM      | -5V to core of chip   | VSM      | -5V to core of chip   |
| 16          | VINP_R   | Red positive differential input   | VINP_R   | Red positive differential input   |
| 17          | VINM_R   | Red negative differential input   | VINM_R   | Red negative differential input   |
| 18          | VINP_G   | Green positive differential input   | VINP_G   | Green positive differential input   |
| 19          | VINM_G   | Green negative differential input   | VINM_G   | Green negative differential input   |
| 20          | VINP_B   | Blue positive differential input  | VINP_B   | Blue positive differential input  |
| 21          | VINM_B   | Blue negative differential input  | VINM_B   | Blue negative differential input  |
| 22          | VSP      | +5V to core of chip   | VSP      | +5V to core of chip   |
| 23          | HOUT     | Decoded horizontal sync referenced to SYNCREF                                       | VCM_R    | Red common-mode voltage at inputs   |
| 24          | VOUT     | Decoded vertical sync referenced to SYNCREF   | VCM_G    | Green common-mode voltage at inputs   |
| 25          | SYNCREF  | Reference level for H <sub>OUT</sub> and V <sub>OUT</sub> logic outputs             | VCM_B    | Blue common-mode voltage at inputs  |
| 26          | X2       | Logic signal for x1/x2 output gain setting  | X2       | Logic signal for x1/x2 output gain setting  |
| 27          | ENABLE   | Chip enable logic signal  | ENABLE   | Chip enable logic signal  |
| 28          | 0V       | 0V reference for output voltage   | 0V       | 0V reference for output voltage   |
| Thermal Pad |          | Must be connected to -5V  |          |   |

**Absolute Maximum Ratings** ( $T_A = +25^\circ\text{C}$ )

|  |  |
|--|--|
| Supply Voltage between $V_{S+}$ and $V_{S-}$ ..... | 12V  |
| Maximum Continuous Output Current per Channel..... | 30mA   |
| Power Dissipation.....                             | See <a href="#">"Typical Performance Curves"</a> |
| Pin Voltages.....                                  | $V_{S-} -0.5\text{V}$ to $V_{S+} +0.5\text{V}$   |
| Storage Temperature.....                           | $-65^\circ\text{C}$ to $+150^\circ\text{C}$      |

**Operating Conditions**

|                                    |  |
|------------------------------------|--|
| Ambient Operating Temperature..... | $-40^\circ\text{C}$ to $+85^\circ\text{C}$ |
| Die Junction Temperature.....      | $+150^\circ\text{C}$                       |

**CAUTION:** Stresses above those listed in "Absolute Maximum Ratings" can permanently damage the device. This is a stress only rating and operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied.

**IMPORTANT NOTE:** All parameters having Min/Max specifications are ensured. Typ values are for information purposes only. Unless otherwise noted, all tests are at the specified temperature and are pulsed tests, therefore:  $T_J = T_C = T_A$

**Electrical Specifications**  $V_{SA+} = V_{A+} = +5\text{V}$ ,  $V_{SA-} = V_{A-} = -5\text{V}$ ,  $T_A = +25^\circ\text{C}$ , exposed die plate =  $-5\text{V}$ , unless otherwise specified.

| PARAMETER   | SYMBOL                       | CONDITIONS  | MIN  | TYP       | MAX  | UNIT              |
|---|------------------------------|---|------|-----------|------|-------------------|
| <b>AC PERFORMANCE</b>                             |                              |   |      |           |      |                   |
| Bandwidth   | BW                           | (See <a href="#">Figure 1</a> )   |      | 150       |      | MHz               |
| Slew Rate   | SR                           | $V_{IN} = -1\text{V}$ to $+1\text{V}$ , $V_G = 0.39$ , $V_C = 0$ ,<br>$R_L = 75 + 75\Omega$                       |      | 1.5       |      | kV/ $\mu\text{s}$ |
| Total Harmonic Distortion                         | THD                          | 10MHz 2V <sub>P-P</sub> out, $V_G = 1\text{V}$ , X2 gain,<br>$V_C = 0$  |      | -50       |      | dBc               |
| <b>DC PERFORMANCE</b>                             |                              |   |      |           |      |                   |
| Offset Voltage                                    | $V(V_{OUT})_{OS}$            | X2 = high, no equalization  | -110 | -15       | +110 | mV                |
| Channel-to-Channel Offset Matching                | $\Delta V_{OS}$              | X2 = high, no equalization  | -140 | 0         | +140 | mV                |
| <b>INPUT CHARACTERISTICS</b>                      |                              |   |      |           |      |                   |
| Common-Mode Input Range                           | CMIR                         |   |      | -4/+3.5   |      | V                 |
| Output Noise                                      | $O_{NOISE}$                  | $V_G = 0\text{V}$ , $V_C = 0\text{V}$ , X2 = HIGH,<br>$R_{LOAD} = 150\Omega$ , Input 50 $\Omega$ to GND,<br>10MHz |      | -110      |      | dBm               |
| Common-Mode Rejection Ratio                       | CMRR                         | Measured at 10kHz   |      | -80       |      | dB                |
| Common-Mode Rejection Ratio                       | CMRR                         | Measured at 10MHz   |      | -55       |      | dB                |
| CM Amplifier Bandwidth                            | CMBW                         | 10k    10pF load  |      | 50        |      | MHz               |
| CM Slew Rate                                      | $CM_{SLEW}$                  | Measured at $+1\text{V}$ to $-1\text{V}$  |      | 100       |      | V/ $\mu\text{s}$  |
| Differential Input Capacitance                    | $C_{INDIFF}$                 | Capacitance $V_{INP}$ to $V_{INM}$  |      | 600       |      | fF                |
| Differential Input Resistance                     | $R_{INDIFF}$                 | Resistance $V_{INP}$ to $V_{INM}$   | 1    |           |      | M $\Omega$        |
| CM Input Capacitance                              | $C_{INCM}$                   | Capacitance $V_{INP} = V_{INM}$ to GND  |      | 1.2       |      | pF                |
| CM Input Resistance                               | $R_{INCM}$                   | Resistance $V_{INP} = V_{INM}$ to GND   | 1    |           |      | M $\Omega$        |
| Positive Input Current                            | $+I_{IN}$                    | DC bias at $V_{INP} = V_{INM} = 0\text{V}$  |      | 1         |      | $\mu\text{A}$     |
| Negative Input Current                            | $-I_{IN}$                    | DC bias at $V_{INP} = V_{INM} = 0\text{V}$  |      | 1         |      | $\mu\text{A}$     |
| Differential Input Range                          | $V_{INDIFF}$                 | $V_{INP} - V_{INM}$ when slope gain falls to 0.9  | 2.5  |           |      | V                 |
| <b>OUTPUT CHARACTERISTICS</b>                     |                              |   |      |           |      |                   |
| Output Voltage Swing                              | $V(V_{OUT})$                 | $R_L = 150\Omega$   |      | $\pm 3.5$ |      | V                 |
| Output Drive Current                              | $I(V_{OUT})$                 | $R_L = 10\Omega$ , $V_{INP} = 1\text{V}$ , $V_{INM} = 0\text{V}$ ,<br>X2 = high, $V_G = 0.39$                     | 50   | 60        |      | mA                |
| CM Output Resistance of VCM_R/G/B (ISL59913 only) | $R(V_{CM})$                  | At 100kHz   |      | 30        |      | $\Omega$          |
| Gain  | Gain                         | $V_C = 0$ , $V_G = 0.39$ , X2 = 5, $R_L = 150\Omega$  | 0.85 | 1.0       | 1.1  |                   |
| Channel-to-Channel Gain Matching                  | $\Delta\text{Gain at DC}$    | $V_C = 0$ , $V_G = 0.39$ , X2 = 5, $R_L = 150\Omega$  |      | 3         | 8    | %                 |
| Channel-to-Channel Gain Matching                  | $\Delta\text{Gain at 15MHz}$ | $V_C = 0.6$ , $V_G = 0.39$ , X2 = 5, $R_L = 150\Omega$ ,<br>Frequency = 15MHz                                     |      | 3         | 11   | %                 |

**Electrical Specifications**  $V_{SA^+} = V_{A^+} = +5V$ ,  $V_{SA^-} = V_{A^-} = -5V$ ,  $T_A = +25^{\circ}C$ , exposed die plate =  $-5V$ , unless otherwise specified.

| PARAMETER   | SYMBOL                | CONDITIONS  | MIN                        | TYP | MAX                 | UNIT |
|---|-----------------------|---|----------------------------|-----|---------------------|------|
| High Level output on V/H <sub>OUT</sub> (ISL59910 only) | V(SYNC) <sub>HI</sub> |   | V(V <sub>SP</sub> ) - 0.1V |     | V(V <sub>SP</sub> ) |      |
| Low Level output on V/H <sub>OUT</sub> (ISL59910 only)  | V(SYNC) <sub>LO</sub> |   | V(SYNCREF)                 |     | V(SYNCREF) + 0.1V   |      |
| <b>SUPPLY</b>   |                       |   |                            |     |                     |      |
| Supply Current per Channel                              | I <sub>SON</sub>      | V <sub>ENBL</sub> = 5, V <sub>INM</sub> = 0                           | 32                         | 36  | 39                  | mA   |
| Supply Current per Channel                              | I <sub>SOFF</sub>     | V <sub>ENBL</sub> = 0, V <sub>INM</sub> = 0                           | 0.2                        |     | 0.4                 | mA   |
| Power Supply Rejection Ratio                            | PSRR                  | DC to 100kHz, ±5V supply  |                            | 65  |                     | dB   |
| <b>LOGIC CONTROL PINS (ENABLE, X2)</b>                  |                       |   |                            |     |                     |      |
| Logic High Level  | V <sub>HI</sub>       | V <sub>IN</sub> - V <sub>LOGIC</sub> reference for ensured high level | 1.4                        |     |                     | V    |
| Logic Low Level   | V <sub>LOW</sub>      | V <sub>IN</sub> - V <sub>LOGIC</sub> reference for ensured low level  |                            |     | 0.8                 | V    |
| Logic High Input Current                                | I <sub>LOGICH</sub>   | V <sub>IN</sub> = 5V, V <sub>LOGIC</sub> = 0V                         |                            |     | 50                  | μA   |
| Logic Low Input Current                                 | I <sub>LOGICL</sub>   | V <sub>IN</sub> = 0V, V <sub>LOGIC</sub> = 0V                         |                            |     | 15                  | μA   |

**Typical Performance Curves**




FIGURE 1. FREQUENCY RESPONSE OF ALL CHANNELS




FIGURE 2. GAIN vs FREQUENCY ALL CHANNELS




FIGURE 3. GAIN vs FREQUENCY FOR VARIOUS V<sub>CTRL</sub>




FIGURE 4. GAIN vs FREQUENCY FOR VARIOUS V<sub>CTRL</sub> AND V<sub>GAIN</sub>

**Typical Performance Curves** (Continued)




FIGURE 5. GAIN vs FREQUENCY FOR VARIOUS  $V_{CTRL}$  AND CABLE LENGTHS




FIGURE 6. CHANNEL MISMATCH




FIGURE 7. OFFSET vs  $V_{CTRL}$




FIGURE 8. DC GAIN vs  $V_{GAIN}$




FIGURE 9. HARMONIC DISTORTION vs FREQUENCY




FIGURE 10. OUTPUT NOISE

**Typical Performance Curves** (Continued)




FIGURE 11. COMMON-MODE REJECTION




FIGURE 12. CM AMPLIFIER BANDWIDTH




FIGURE 13. (+)PSRR vs FREQUENCY




FIGURE 14. (-)PSRR vs FREQUENCY




FIGURE 15. BLUE CROSSTALK (CABLE LENGTH = 3ft.)




FIGURE 16. BLUE CROSSTALK (CABLE LENGTH = 600ft.)

**Typical Performance Curves** (Continued)




FIGURE 17. GREEN CROSSTALK (CABLE LENGTH = 3ft.)




FIGURE 18. GREEN CROSSTALK (CABLE LENGTH = 600ft.)




FIGURE 19. RED CROSSTALK (CABLE LENGTH = 3ft.)




FIGURE 20. RED CROSSTALK (CABLE LENGTH = 600ft.)




FIGURE 21. RISE TIME AND FALL TIME




FIGURE 22. PULSE RESPONSE FOR VARIOUS CABLE LENGTHS

## Typical Performance Curves (Continued)




FIGURE 23. PACKAGE POWER DISSIPATION vs AMBIENT TEMPERATURE




FIGURE 24. PACKAGE POWER DISSIPATION vs AMBIENT TEMPERATURE

## Applications Information

### Logic Control

The ISL59913 has two logical input pins, Chip Enable (ENABLE) and Switch Gain (X2). The logic circuits all have a nominal threshold of 1.1V above the potential of the logic reference pin (VREF). In most applications it is expected that this chip runs from a +5V, 0V, -5V supply system with logic being run between 0V and +5V. In this case, tie the logic reference voltage to the 0V supply. If the logic is referenced to the -5V rail, connect the logic reference to -5V. The logic reference pin sources about 60 $\mu$ A and this rises to about 200 $\mu$ A if all inputs are true (positive).

The logic inputs all source up to 10 $\mu$ A when they are held at the logic reference level. When taken positive, the inputs sink a current dependent on the high level, up to 50 $\mu$ A for a high level 5V above the reference level.

If the logic inputs are not used, tie them to the appropriate voltage to define their state.

### Control Reference and Signal Reference

Analog control voltages are required to set the equalizer and contrast levels. These signals are voltages in the range 0V to 1V, which are referenced to the control reference pin. It is expected that the control reference pin is tied to 0V and the control voltage varies from 0V to 1V. It is, however, acceptable to connect the control reference to any potential between -5V and 0V to which the control voltages are referenced.

The control voltage pins themselves are high impedance. The control reference pin sources between 0 $\mu$ A and 200 $\mu$ A depending on the control voltages being applied.

The control reference and logic reference effectively remove the necessity for the 0V rail and operation from  $\pm$ 5V (or 0V and 10V) only is possible. However, we still need a further reference to

define the 0V level of the single-ended output signal. The reference for the output signal is provided by the 0V pin. The output stage cannot pull fully up or down to either supply so it is important that the reference is positioned to allow full output swing. Tie the 0V reference to a quiet reference as any noise on this pin is transferred directly to the output. The 0V pin is a high impedance pin and draws DC bias currents of a few  $\mu$ A and similar levels of AC current.


### Equalizing

When transmitting a signal across a twisted pair cable, the high frequency (above 1MHz) information is attenuated more significantly than the information at low frequencies. The attenuation is predominantly due to resistive skin effect losses and has a loss curve which depends on the resistivity of the conductor, surface condition of the wire, and the wire diameter. For the range of high performance twisted pair cables based on 24awg copper wire (CAT-5 etc), these parameters vary only a little between cable types and in general cables exhibit the same frequency dependence of loss. (The lower loss cables can be compared with somewhat longer lengths of similar cables.) This enables a single equalizing law equation to be built into the ISL59913.

With a control voltage applied between pins VCTRL and VREF, the frequency dependence of the equalization is shown in [Figure 8 on page 6](#). The equalization matches the cable loss up to about 100MHz. Above this, system gain is rolled off rapidly to reduce noise bandwidth. The roll-off occurs more rapidly for higher control voltages, thus the system (cable + equalizer) bandwidth reduces as the cable length increases. This is desirable, as noise increases as the equalization increases.

**Contrast**

By varying the voltage between pins VGAIN and VREF, the gain of the signal path can be changed in the ratio 4:1. The gain change varies almost linearly with control voltage. For normal operation it is anticipated the X2 mode is selected and the output load is back matched. A unity gain to the output load is achieved with a gain control voltage of about 0.35V. This allows the gain to be trimmed up or down by 6dB to compensate for any gain/loss errors that affect the contrast of the video signal. [Figure 25](#) shows an example plot of the gain to the load with gain control voltage.




**FIGURE 25. VARIATION OF GAIN WITH GAIN CONTROL VOLTAGE**

**Common-Mode Sync Decoding**

The ISL59910 features common-mode decoding to allow horizontal and vertical synchronization information, which has been encoded on the three differential inputs by the EL4543, to be decoded. The entire RGB video signal can therefore be transmitted, along with the associated synchronization information, by using just three twisted pairs.

Decoding is based on the EL4543 encoding scheme, as described in [Figure 26](#) and [Table 1](#). The scheme is a three-level system, which has been designed such that the sum of the common-mode voltages results in a fixed average DC level with no AC content. This eliminates the effect of EMI radiation into the common-mode signals along the twisted pairs of the cable

The common-mode voltages are initially extracted by the ISL59910 from the three input pairs. These are then passed to an internal logic decoding block to provide Horizontal and Vertical sync output signals (H<sub>OUT</sub> and V<sub>OUT</sub>).



**FIGURE 26. H AND V SYNCs ENCODED**

**TABLE 1. H AND V SYNC DECODING**

| RED CM | GREEN CM | BLUE CM | H <sub>SYNC</sub> | V <sub>SYNC</sub> |
|--------|----------|---------|-------------------|-------------------|
| Mid    | High     | Low     | Low               | Low               |
| High   | Low      | Mid     | Low               | High              |
| Low    | High     | Mid     | High              | Low               |
| Mid    | Low      | High    | High              | High              |

NOTE: Level 'Mid' is halfway between 'High' and 'Low'

**Power Dissipation**

The ISL59910 and ISL59913 are designed to operate with ±5V supply voltages. The supply currents are tested in production and specified to be less than 39mA per channel. Operating at ±5V power supply, the total power dissipation is:

$$PD_{MAX} = 3 \times \left[ 2 \times V_S \times I_{SMAX} + (V_S - V_{OUTMAX}) \times \frac{V_{OUTMAX}}{R_L} \right] \tag{EQ. 1}$$

where:

- PD<sub>MAX</sub> = Maximum power dissipation
- V<sub>S</sub> = Supply voltage = 5V
- I<sub>SMAX</sub> = Maximum quiescent supply current per channel = 39mA
- V<sub>OUTMAX</sub> = Maximum output voltage swing of the application = 2V
- R<sub>L</sub> = Load resistance = 150Ω

$$PD_{MAX} = 1.29W \tag{EQ. 2}$$

$\theta_{JA}$  required for long term reliable operation can be calculated using [Equation 3](#):

$$\theta_{JA} = \frac{(T_J - T_A)}{PD} = 50.4 \text{CW} \quad (\text{EQ. 3})$$

where

- $T_J$  is the maximum junction temperature (+150°C)
- $T_A$  is the maximum ambient temperature (+85°C)

For a QFN 28 package in a properly laid out PCB heatsinking copper area, +37°C/W  $\theta_{JA}$  thermal resistance can be achieved. To disperse the heat, the bottom heatspreader must be soldered to the PCB. Heat flows through the heatspreader to the circuit board copper, then spreads and converts to air. Thus the PCB copper plane becomes the heatsink. This has proven to be a very effective technique.

**Revision History** The revision history provided is for informational purposes only and is believed to be accurate, but not warranted. Please visit our website to make sure you have the latest revision.

| DATE         | REVISION | CHANGE  |
|--------------|----------|---|
| Sep 28, 2018 | FN6406.1 | Added Related Literature section.<br>Moved Pinouts after Ordering Information table.<br>Updated Ordering Information table by updating brand for ISL59913 parts, adding Notes 1 and 3, adding Evaluation boards, updating POD number, and updating tape and reel column.<br>Added Revision History.<br>Updated disclaimer and moved to end of document.<br>Updated POD from MDP0046 to L28.4x5. |



## Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
5. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.  
"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.  
"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.  
Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.
6. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
7. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
8. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
9. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
10. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
11. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
12. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.4.0-1 November 2017)



### SALES OFFICES

Renesas Electronics Corporation

<http://www.renesas.com>

Refer to "<http://www.renesas.com>" for the latest and detailed information.

#### Renesas Electronics Corporation

TOYOSU FORESIA, 3-2-24 Toyosu, Koto-ku, Tokyo 135-0061, Japan

#### Renesas Electronics America Inc.

1001 Murphy Ranch Road, Milpitas, CA 95035, U.S.A.  
Tel: +1-408-432-8888, Fax: +1-408-434-5351

#### Renesas Electronics Canada Limited

9251 Yonge Street, Suite 8309 Richmond Hill, Ontario Canada L4C 9T3  
Tel: +1-905-237-2004

#### Renesas Electronics Europe Limited

Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K  
Tel: +44-1628-651-700

#### Renesas Electronics Europe GmbH

Arcadiastrasse 10, 40472 Düsseldorf, Germany  
Tel: +49-211-6503-0, Fax: +49-211-6503-1327

#### Renesas Electronics (China) Co., Ltd.

Room 1709 Quantum Plaza, No.27 ZhichunLu, Haidian District, Beijing, 100191 P. R. China  
Tel: +86-10-8235-1155, Fax: +86-10-8235-7679

#### Renesas Electronics (Shanghai) Co., Ltd.

Unit 301, Tower A, Central Towers, 555 Langao Road, Putuo District, Shanghai, 200333 P. R. China  
Tel: +86-21-2226-0888, Fax: +86-21-2226-0999

#### Renesas Electronics Hong Kong Limited

Unit 1601-1611, 16/F., Tower 2, Grand Century Place, 193 Prince Edward Road West, Mongkok, Kowloon, Hong Kong  
Tel: +852-2265-6688, Fax: +852 2886-9022

#### Renesas Electronics Taiwan Co., Ltd.

13F, No. 363, Fu Shing North Road, Taipei 10543, Taiwan  
Tel: +886-2-8175-9600, Fax: +886 2-8175-9670

#### Renesas Electronics Singapore Pte. Ltd.

80 Bendemeer Road, Unit #06-02 Hyflux Innovation Centre, Singapore 339949  
Tel: +65-6213-0200, Fax: +65-6213-0300

#### Renesas Electronics Malaysia Sdn.Bhd.

Unit 1207, Block B, Menara Amcorp, Amcorp Trade Centre, No. 18, Jin Persiaran Barat, 46050 Petaling Jaya, Selangor Darul Ehsan, Malaysia  
Tel: +60-3-7955-9390, Fax: +60-3-7955-9510

#### Renesas Electronics India Pvt. Ltd.

No.777C, 100 Feet Road, HAL 2nd Stage, Indiranagar, Bangalore 560 038, India  
Tel: +91-80-67208700, Fax: +91-80-67208777

#### Renesas Electronics Korea Co., Ltd.

17F, KAMCO Yangjae Tower, 262, Gangnam-daero, Gangnam-gu, Seoul, 06265 Korea  
Tel: +82-2-558-3737, Fax: +82-2-558-5338

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Renesas Electronics:](#)

[ISL59910IRZ](#) [ISL59910IRZ-T7](#) [ISL59913IRZ](#) [ISL59913IRZ-T7](#)